

# Chainsaw Spark Plug Application Chart

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>CRAFTSMAN/SEARS</b>						
<b>Chainsaws</b>						
1.9S, 2.0, 2.1A, 271-1.8, 271-2.7A/VL, 3.6, 3400, 3401, 3402, 3408, 3411, 3412, 3415, 3416, 3418, 3425, 3455, 3460, 3461, 3465, 34663476, 3481, 34071, 3409435082, 35091, 35093, 34094, 35096, 35201, 35202, 35177, 35187, 3119735203, 35205, 35206, 352030, 352060, 352070, 352090, 35207, 35209, 35232, 35211, 35215, 352231, 352351, 35265C, 35238, 35251, 35255, 35251, 35256, 35263, 35266, 35267, 3537135363, 35366, 35367, 35369, 35373C, 35377C, 35481, 35483, 35487, 35505, 35506, 35512, 35514, 35515, 35516, 36096, 36212, 36235, 357120, 357160, 358810, 358840, 35883, 35887, 35889, 358860, 36212, 59716, 59741, 59816, 59886, 714.3A/VL	0.030	CJ8/130-094	BM6A/130-799	SE-CJ8/130-096	L6TC/131-027	
3.7, 3.7A, 3.7PS, 35158, 35147, 35148, 35171, 35372, 35373, 35375, 35376, 35607, 35628, 35633, 35718, 35886, 35904, Beaver 1.9	0.030	CJ6/130-098	BM7A/130-864		L7TC/131-003	
35269, 35365, 35505	0.025	DJ8J/130-071	BM6F/130-807			
35484, 35608, 35609, 35885, 358356, 35881, 35889, 358850	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
59820, 59918	0.030	RCJ7Y/130-241	BPMP6A/130-815			
<b>DOLMAR</b>						
<b>Chainsaws</b>						
103, 105, 108, PS3300TH	0.030	RCJ8/130-091	BMR6A/130-690			
109, 110, 110i, 111, 111i, 112, 113, 114, 115, 115i, 116, 116Si, 117, 118, 119, 120, 120 Super, 120Si, 122, 123, 128 KMS4 Rotary, 133, 133 Super, 143, 144, 152, 153, 166, 310, PS-460, PS-510, PS-5100S, PS-540, PS-6000i, PS-6400, PS-6800i, PS-7300, PS-7900, PS-9000, PS-9010, PS-9010i, PS34, PS342	0.020	RCJ6Y/130-073	BPMP7A/130-898		L7RTC/131-023	WR6F/130-124
309, 343	0.020	RCJ7Y/130-241	BPMP6A/130-815			
<b>ECHO</b>						
<b>Chainsaws</b>						
CS-300, CS-300-14, CS-301, CS-341, CS-346, CS-520, CS-6700, QV-6700	0.025	CJ6Y/130-077	BPM8Y/130-884		L7TC/131-003	WS7F/130-120
CS-305, CS-330T, CS-340, CS-345, CS-360T, CS-440, CS-520, 3900, 4400, 4500, 4600, 5000, 510EVL, 5500, 660EVL, 6700, 702EVL, 702VL, 750EVL, 8000	0.025	RCJ6Y/130-073	BPMP8Y/130-115		L7RTC/131-023	WR6F/130-124
CS-3000, CS-3400, CS-3540, CS-4400, CS-5000, CS-510, CS-520, CS-8000, QV-670, QV-675, QV-6750, QV8000, QV-8050	0.025	CJ7Y/130-075	BPM7A/130-880	SE-CJ7Y/130-146		WS7F/130-120
100, 280EP, 300EVL, 301, 302, 302S, 304, 315, 330, 351VL, 451VL, 452VL, 601, 601S, 601SVL, 602EVL, 60S, 650EVL, 701SVL, 701VL, 801, 802, 80Z, S290	0.025	RCJ8/130-091	BMR6A/130-690			

\* Net Priced Item

## Chainsaw Spark Plug Application Chart

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>ECHO (Cont.)</b>						
<b>Chainsaws (Cont.)</b>						
1001VL, 2800, 2900, 290EVL, 290EVL, 3000, 330EVL, 330EVL, 3400, 3450, 4000, 4000EVL, 410EVL, 440EVL, 440EVL, 410EVL, 440EVL, 440EVL, 510EVL, 550EVL, 601EVL, 602VL, 610EVL, 620VL, 650EVL, 660EVL, 660VL, 750EVL, 852EVL, 900EVL	0.025	RCJ7Y/130-241	BPMR6A/130-815			
280E, 290EVL, 300EVL, 400EVL, 500EVL	0.025	RCJ8Y/130-079	BPM7Y/130-785	SE-CJ7Y/130-146	L6RTC/131-051	
<b>HOMELITE</b>						
<b>Chainsaws</b>						
1010, 1050, 1130G, 2100 Super, 2100S, 3100G, 35SL, 650, 750, 945, 955, Big Red SXL, Old Blue SXL, DM-20 Multi-Purpose, DM-50 Multi-Purpose, MP38, MP88 Multi-Purpose, Super 1050, Super 1130G, Super XL, Super XL-925, Super XL-AO, V1123, XL123, XL660F, XL923, XL923A, XL924A, XL925, V1-944, V1-955, XL98D Multi-Purpose	0.025		BM7A/130-864		L7TC/131-003	
150, 190, 240, Super 240, Super-2, V1-Super-2, XL, XL-2	0.025	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
180, 192, 200, 245HG, SL, 252, 540, CS-40, DM-40, DM-54 Multi-Purpose, LX30, Little Red XL	0.025	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
250, 290, 300, 340, 8800, z2240b, z3850b, z3330, z3350	0.025	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	W-S7F/130-120
C72, Super Wiz 55, Super Wiz 66, Super Wiz 80	0.025	J8C/130-093	B6S/130-781	SE-CJ8/130-096		
XL-12, XL100A	0.025	CJ8/130-094	BM6A/130-799	SE-CJ8/130-096	L6TC/131-027	
<b>HUSQVARNA</b>						
<b>Chainsaws</b>						
136, 141, 20PS, 261, 2101XP, 2405, 23 Compact, 242XP, 244, 254XPG, 260CD, 254XP, 257, 260, 262XPG, 263CD, 266SG, 266XP, 262XP, 266SE, 272XPG, 280G, 281, 268, 26RCL, 32R, 32RCL, 32, 165RX, 272XP, 281XP, 285CD, 185CD, 1100CD, 2100CD, 3130, 288XP, 3120XP, 33, 34, 335XP, 335XPT, 380S, 480CD, 280S, 280CD, 340, 340SE, 340SG, 380CD, 345, 346XP, 350, 351, 353, 357XP, 359, 36, 365, 371XPG, 394XPG, 371XP, 372XP, 385XP, 394XP, 395XP, 40, 41, 42, 44, 444, 444SE, 444SG, 444FE, 444FG, 480K, 45, 49, 50, 65, 51, 55, 55 Rancher, 61 66, 77, A77, B77, L77, S77, Husky 246, Husky 35VR, Husky 36R, Husky 38, Husky 39R, Husky A65, Husky B65	0.020	RCJ7Y/130-241	BPMR7A/130-898		L7RTC/131-023	W-SR6F/130-124

\* Net Priced Item

# Chainsaw Spark Plug Application Chart

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>HUSQVARNA (Cont.)</b>						
<b>Chainsaws (Cont.)</b>						
140, 140S, 154, 160CD, 160SG, 162FE, 162FG, 162SE, 162SG, 163S, 163SE, 165, 165R, 180S, 1R, 16, 18, 22R, 22RL, 24, 25RL	0.020	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
2100CDW, 35, 37, Husky 22, Husky 23, Compact 35, Compact 37	0.020		BM7A/130-864		L7TC/131-003	
A100, G90, SM150	0.020	L86C/130-085	B6HS/130-712			
<b>JOHN DEERE</b>						
<b>Chainsaws</b>						
12, 14, 15, 17, 18, 19, 23, 350CS, 61, 8, 9, 81, 82, 91	0.030		BM7A/130-864		L7TC/131-003	
200CS, 230CS, 550CS, 820, 840	0.030	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	W-S7F/130-120
25EV, 46EV, 51SV, 55EV, 65EV, 300CS, 55V, 60V, 65SV, 66SV, 450V, 800V, 70V, 72, 80EV, R70EV, S80, S82	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
28, 30, 35EV, 40V, 50, 50V	0.030	CJ8/130-094	BM6A/130-799	SE-CJ8/130-096	L6C/131-011	W-S8E/130-112
<b>JONSERED</b>						
<b>Chainsaws</b>						
111S, 435, 450, 2036, 2040, 2041 Turbo, 2045, 2050, 2051 Turbo, 2051, 2054, 2055 Turbo, 2055 Cat, 2063, 2065, 2071 Turbo, 2071W, 2077, 2083 Turbo, 2094, 2095 Turbo, 451EV, 521EV, 525, 535, 45ES, 49SP, 52ES, 66E, 590, 621, 625 II, 630 Super II, 630S, 670 Champ, 801, 830, 910D, 66ES, 70E, 90W, 910E, 920, 930S, BadNSaw Mill 6000+, HP36 Power Pruner, M50, M80, M110, M52, M510SP, M60, M62, M601, M621, M75, M751, Mini Sawmill 600+, MK70, MK80, RS45, Pro 35, Super III	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
410, 420, 490, 510, 510M, 520SP	0.030	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
365, L1L-J, M36, M361, M361AV	0.030	J8C/130-093	B6S/130-781	SE-CJ8/130-096		
820, 840	0.030	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
<b>MAKITA</b>						
<b>Chainsaws</b>						
DCS-330S, DCS-340, DCS-341, DCS-390, DCS-400, DCS-401	0.025	RCJ8Y/130-079	BPMR6A/130-815		L6RTC/131-051	
DCS-430, DCS-431, DCS-5200i, DCS-520i, DCS-6800iFL/FW, DCS-9000FL/FW, DCS342, DCS391, DPC-7000, DPC-7001, DPC-9500, DPC-9501, DPC6200, DPC6201, DPC7003, DPC7301	0.025	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WR6F/130-124

CHAINSAW PARTS

\* Net Priced Item

## Chainsaw Spark Plug Application Chart

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>MCCULLOCH</b>						
<b>Chainsaws</b>						
1.9, 2.3, Titan 560, Titan 620	0.025	RCJ7Y/130-241	BPMR6A/130-815			
10-10, 10-10A, 10-10L, 3-10, 3-10E, 895, Double Eagle (50, 80) Eager Beaver (10, 12, 14, 16, 2.0, 2.1, 2.3, 3.4, 3.7) Mac (100, 110), Pro Mac (40, 4700AV, 5000, 510, 555, 570, 5700AV, 5720, 605, 610, 650, 690, 700) S10-10, S10-10LA 795, S10-10LA 795L, S10-10LA 797, S10-10LA S797, S2-10A	0.025	DJ8J/130-071	BM6F/130-807	SE-J8D/130-138		
250, 550, 650, 660, 940, S250, S550	0.025	J8C/130-093				
5-10A, 5-10G, 6-10, 6-10A, 7-10A, CP-125, CP-125S, CP-70, CP-70L, G-70, LG-6, Mac 10 series, 4-10, 5-10, PM-60, Pro Mac (3800, 800, 8200, 850) S6-10A, SP105, AP125C, SP40, SP60, SP80, SP81	0.025	DJ6J/130-101				
Eager Beaver (2000, 2100AV, Super 2300AV) Mac (3200 series, 3500AV series, 3800AV series) Mac Cat (16, 18) MS1432, MS1635, MS1635AV, MS1838AV, Pro Mac (2500, 3205AV-14, 3505AV-16, 380)	0.025	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
<b>OLYMPYK</b>						
All Models	0.030	CJ7Y/130-075	BPM7A/130-880	SE-CJ7Y/130-146	L7TC/131-003	WS7F/130-120
<b>PARTNER</b>						
<b>Chainsaws</b>						
1610, 1611, 1612, 1613, 1614, 1614C, 1616, 1616C, 1705, 1712, 933, 944, 946, 947, Partner Mini III, Partner Mini IV	0.030	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
1629, 1630, 1631, 1644, 1645, 1660, 1661, 1690	0.030	J8C/130-093				
1632, 1632C, 1646, 1646C, 1647C, 1655, 1655B, 2055, 2055B	0.030	CJ6/130-098	BM7A/130-864			
F55, F55A, F65, K-12, S65	0.030	L86C/130-085	BP6HS/130-272			
K-20, K-40, R-16, R-17, R-30, TS	0.030	CJ8/130-094	BM6A/130-799	SE-CJ8/130-096	L6TC/131-027	
Mini-P, Mini-P11, Mini-PA, P55, P70, P7000, P85, R-20, R-20T, R-40T, R-44T, R-417T, R-420, R-420T, R-421T, R-435, R-517, R-517T, R-85	0.030	CJ6/130-098	BM7A/130-864		L7TC/131-003	

## Chainsaw Spark Plug Application Chart

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>POULAN</b>						
<b>Chainsaws</b>						
100, 20, 20D, 245A, 25, 252A, 25DA, 25SN, 306, 306A, 306SA, 361, 5200CVA, 71A, 72, 76, 92 Micro MZ5, Micro XXV, Model XX, S25, S25AV, S68, S72, Super XXV	0.025	CJ8/130-094	BM6A/130-799	SE-CJ8/130-096	L6TC/131-027	
180, 1800, 1950, 200, 2000, 205, 2050, 2100, 2150, 2175, 2250, 2300, 2350, 2375, 2400, 2450, 2500, 2550, 2600, 2750, 2900, 3050, 355, 405, 415, 4200CVA, 6000CVA, KS412, P3314, P3314WS, P3416, P4018, P4018WT, PP225, PP190 Arborist, PP210, PP230, PP235, PP236, PP255, PP260, PP295, PP310, PP315, PP405, PP415, PP425, PP445, PP455, PP475, PP505, PP525, PP655, PPS23 Arbor Pro, PPS25DA, S23, S6000, Wild Thing 2175, Wild Thing 2375	0.025	CJ7Y/130-075	BPM7A/130-880	SE-CJ7Y/130-146	L7TC/131-003	WS7F/130-120
3400, 3700, 375, 3800, 4000, PP325, PP375, PP395	0.025	CJ8Y/130-072	BPM4A/130-789		L6TC/131-027	
3500, 3600, 3750, Bad Boy 3750, PP365, PP380	0.025	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
4400, 4900, 5400, 6900, 7700, 8500	0.025	CJ6/130-098	BMR7A/130-864			
53A, 54, S33	0.025	J8C/130-093	B6S/130-781	SE-CJ8/130-096		
<b>STIHL</b>						
<b>Chainsaws</b>						
06, 07, 07S, 08, 08H	0.020		BP6HS/130-272			
All other Stihl models R6F/130-124	0.020	RCJ6Y/130-073	BPMR7A/130-898		L6RTC/131-051	WS-
<b>TANAKA</b>						
<b>Chainsaws</b>						
ECS-290, ECS-300, ECS307, ECS-320, ECS-330, ECS-350, ECS-351, ECS3301, ECS-351, ECS-3301, ECS3351, ECS-35, ECS-35B, ECS-35E, ECS3500B, ECS-355, ECS-356, ECS-357, ECS-370	0.030	CJ8/130-094	BM6A/130-799	SE-CJ8/130-096	L6C/131-011	WS8E/130-112
ECS-405, ECS-415, ECS-505, ECS506, ECS650, ECS-655, ECV-4501, ES-650/20, ES650/24	0.030	CJ8Y/130-072	BPM4A		L6TC/131-027	
EBC-1, ECS-3, ECS-5	0.030		B6S/130-781			
ECV-4501 2.5HP, ECV5601 2HP	0.024	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	