

# Spark Plug Application Chart



## GAS ENGINES

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>BRIGGS &amp; STRATTON</b>						
<b>Force</b>	0.030	RDJ7Y/130-137				
<b>Intek</b> — single and twin cylinder OHV						
<b>Vanguard</b> — liquid cooled three cylinders, single cylinder OHV engines and 31 HP OHV V-twin	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
<b>Single cylinder OHV engines</b> — 97700 series, 99700 series, 197700 series, 28E700 series, 287700 series, 28N700 series, 28U700 series, 28W700						
<b>Vanguard V-twin OHV (27 HP thru 32 HP)</b>	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
<b>Vanguard</b> — V-twin OHV (12.5 HP thru 23 HP) 19A400-19G400 series, 93400 series (with top tank)	0.030	RC14YC/130-530	FR5/130-839			
Opposed twin cylinder "L" head, single cylinder "L" head	0.030	J19LM/130-105	BR2LM/130-902	SE-19J/130-211	G14C/131-007	WR11E0/130-108
625e, 675ex, 725ex series, 625-675 series and Quantum 7.5-6.75 gross HP engines	0.020	RJ19LMC/130-065				
<b>HONDA</b>						
GC135, GC160, GC190	0.030	RN11YC4/130-595	BPR6ES/130-823		F6RTC/131-039	
GC160A, GC190A, GS190A, GSV190A	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
GX22, GX31, GXH50, GXH50U, GX50, GX100U	0.025		CR5HSB/130-340			
GX25, GX25N, GX25NT, GX25T, GX35, GX35T, GX35NT	0.028		CMR5H/130-694			
G30, G35, G40, G41, G42, G80, GS65, GV35	0.028		BR6HS/130-135			
G65, G80	0.030	L86C/130-085	B6HS/130-712			
G100	0.030	CJ14/130-097	BMR4A/130-756	SE-14JC/130-070		
GV100	0.024	CJ14/130-097	BMR4A/130-756	SE-14JC/130-070		
G150 (with Mag), G200, G300, G400	0.030		BR4HS/130-724			
GV150 2029059> (CDI), GV400	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
GV150 2029059 > (mag)	0.030	RCJ8/130-079	BPM6A/130-831	SE-8JC/130-096	L6C/131-011	WS8E/130-112
GV200, GV400	0.025		BMR6A/130-690			
G400	0.030	RL95YC/130-107	BR4HS/130-724			
GX100, GX110, GX120, GX140, GX160, GX200, GX240, GX240, GX270, GX340, GX390, GX610, GX620, GX670 (to 1999)	0.030	RN11YC4/130-595	BPR6ES/130-823		F6RTC/131-039	
GXV110	0.028	RN11YC4/130-595	BR4HS/130-724		F6RTC/131-039	
GXV120, GXV140, GXV160, GXV270, GXV340, GXV390, GXV520, GXV530	0.028		BPR5ES/130-930			
GX630, GX660, GX690, GXV630	0.030		ZFR5F/130-276			
GX670 (from 2000), GXV610, GXV620, GXV670	0.028		ZGR5A/130-835			
GCV135, GCV135A, GCV160, GCV160A, GCV160E, GCV190, GCV190A, GCV520U	0.030	RN11YC4/130-595	BPR6ES/130-823		F6RTC/131-039	
GXV50, GXV50U, GXV57U	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
GCV530, GCV530U	0.030	RN11YC4/130-595	BPR5ES/130-930		F6RTC/131-039	

\* Net Priced Item

# Spark Plug Application Chart



## GAS ENGINES [Cont.]

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>KAWASAKI</b>						
FA76D (from 1983)	0.028	CJ8/130-094	BM4A/130-708			WS8E/130-112
FA76D (to 1982), KT12, KT15, KT18, KT28	0.024	CJ8/130-094	BM6A/130-799			WS8E/130-112
FA130D, FA210D, FD501D, FD501V (to 1998), FD590V	0.025	RCJ8/130-091	BMR6A/130-690	SE-8JC/130-096	L6C/131-011	WS8E/130-112
FE120D, FE170D, FE250D, FE290D, FE350D, FE400D, FH741D, FH770D, FC150V, FC180V, FC290V, FJ180V, FC401V, FJ400D, FC420V, FC540V	0.028	RN11YC4/130-595	BPR5ES/130-930		F6RTC/131-039	WR8DC/130-154
FD620V, FD661D, FB460V, TF22	0.024	CJ14/130-070	BMR4A/130-756	SE-14JC/130-070		
FD440V, FD501V (From 2002), FD611V						
FD661V, FA210V, TG28	0.025	RCJ8/130-091	BMR6A/130-690	SE-8JC/130-096	L6C/131-011	WS8E/130-112
FD501V (1999-2001), FD680V, FD731V	0.028		BPR4ES/130-938			
FD601V, FD641V, FD671V, FD711D, FD750D, FD791D	0.025		BPR2ES/130-934			
FH381V, FH430V, FH451V, FH500V, FH531V, FH541V, FH580V, FH411V, FH480V, TH26, TEX45, TH23	0.028	RCJ8Y/130-079	BPMR4A/130-716	SE-8JC/130-096	L6C/131-011	WS8E/130-112
FH601D, FH601V, FH641D, FH641V, FH680D, FH680V, FH721D, FH721V	0.028		BPR4ES/130-938			
FR541, FR600V, FR691V, FR730V	0.028		BPR4ES/130-938			
FS481V, FS541V, FS651V, FS691V, FS730V	0.028		BPR4ES/130-938			
FX481V, FX541V, FX600V, FX651V, FX691V, FX730V, FX801V, FX850V	0.028		BPR4ES/130-938			
FX921V, FXT00V	0.028	RN11YC4/130-595	BPR5ES/130-930		F6RTC/131-039	WR8DC/130-154
FJ100D	0.028		BR6HS/130-135			
KF24, KF52, KF53, KF53A, KT43	0.024	L86C/130-085	B6HS/130-712			
KF34, KF68, KF81, KT15J, KT18J, KT18M, KT28G, KT28M, KT28N, KT30, KT30G, KT30J, KT30M, KT30N, TA36, TA51	0.024	J8C/130-093	B6S/130-781			
FG150, FG200, FG270, FG300	0.028	RL95YC/130-107	BP4HS/130-868			
KT10, KT12AD, KT12J, KT12K, KT15D, KT17, KT17J, TA33	0.024	CJ6/130-098	BM7A/130-864			
TEX54	0.026	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
<b>KOHLER</b>						
<b>Aegis Series liquid cooled</b>						
LV560, LV625, LV630, LV675, LV680, LH630, LH685, LH690, LH750, LH755, LH775	0.030	RC14YC/130-530	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
<b>Command/Command Pro Series</b>						
CS4, CS6, CS8.5, CS10, CS12, CS12.75 Hydro, CS13 Hydro	0.030		BPR4ES/130-938			
CH16, CV460, CV490, CV492, CV493, CV17, CH18, CV18, CH20, CV20, CH22, CV22, CH23, CV23, CH25, CH270, CH395, CH730, CV730, CH26, CH27, CH740, CV740, CH745, CV745, CH750, CH940, CV940, CH960, CV960, CH980, CV980, CV1000	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	

\* Net Priced Item

# Spark Plug Application Chart



## GAS ENGINES (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>KOHLER (Cont.)</b>						
CH5, CH6, CH11, CH12.5, CH13, CH14, CH15, CV11, CV12.5, CV13, CV14, CV15	0.040	RC12YC/130-526		SE-12RCY/130-191	K5RTC/131-015	
<b>Courage Series</b>						
SV470, SV480, SV530, SV540, SV590, SV600, SV610, SV620, SV710, SV715, SV720, SV725, SV730, SV735, SV740, SV810, SV820, SV830, SV840	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
XT-6, XTR6, XT-7T	0.030	RA8HC/130-020		SE-12RCY/130-191	K5RTC/131-015	
XT-7, XTR-7	0.030	RA8HC/130-020	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
<b>Magnum Series</b>						
M8	0.025	RCJ8/130-091				
M10, M12, M14, M16, MV23	0.030	RH10C/130-102	B6L/130-773			
MV16, M18, M18V, M20, MV20V	0.025	RV17YC/130-083	UR4/130-740			
<b>Triad</b>						
TH14, TH16, TH18	0.040	RC12YC/130-526		SE-12RCY/130-191	K5RTC/131-015	
<b>K-Series</b>						
K7, K12	0.025	RJ12C/130-087				
K90, K91, K121, K141, K161, L161, K181, L181, K330, K331, K660, K662	0.025	RJ19LM/130-106	B2LM/130-777	SE-19J/130-211	G14C/131-007	WR11E0/130-108
K241, K301, K321, K341, K361, K482, K532, K582 (Twin)	0.0305	RH10C/130-102	B6L/130-773			
KT17 (Twin), KT19 (Twin), KT20 (Twin), KT21 (Twin)	0.025	RV17YC/130-083	UR4/130-740			
KL25	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
<b>LCT</b>						
All engines	0.030				F6RTC/131-039	
<b>SUBARU</b>						
<b>EC Series Air-Cooled 1 Cyl. 2-Stroke</b>						
EC01ER, EC02ER, EC22GR, EC25GR	0.024	CJ6/130-098	BM7A/130-864			
EC03ER, EC04ER	0.024	CJ6Y/130-077	BPM7A/130-880			
EC05-2 D/B, EC06 D/B, EC07-2 D/B, EC08 D/B, EC25 D/DS	0.024	L86C/130-085	B6HS/130-712			
EC12D, EC13V	0.024	CJ8/130-094	BM6A/130-799			WS8E/130-112
<b>EY Series Air-Cooled 1 Cyl 4-Stroke Side Valve</b>						
EY08 D/BN	0.024	CJ14/130-097	BMR4A/130-756	SE-14JC/130-070		
EY10 D/B, EY13-2 D/B, EY14 D/B, EY25 D/B, EY27-2 D/B	0.024	L86C/130-085	B6HS/130-712			
EY15 D/DS, EY15-2 B, EY18-3 D/B, EY20 D/DS/B/BS	0.024		BR6HS/130-135			
EY23 D/DB/B/BS, EY35 D/DB/B/BS, EY40 D/DS/B/BS	0.024	RL95YC/130-107	BPR4HS/130-942			
EY28 D/DS/B/BS	0.024	L86C/130-085	BP6HS/130-272			
EY45V	0.024	RCJ8/130-079	BPM6A/130-831	SE-8JC/130-096	L6C/131-011	WS8E/130-112
<b>EY Series Air-Cooled 2 Cyl. 4-Stroke Side Valve</b>						
EY21 AS/AS-C, EY21 AS-R/AS-CR, EY80-3 AS/AS-C, EY80-3 AS-R/AS-CR	0.024	RL95YC/130-107	BPR4HS/130-942			
<b>EH Series Air-Cooled 1 Cyl. 4-Stroke OHV</b>						
EH025, EH035V	0.024		CMR6A/130-797			

\* Net Priced Item

## Spark Plug Application Chart


**GAS ENGINES** (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>SUBARU (Cont.)</b>						
EH09, EH12 D/DS/B/BS, EH30 D/DS/B/BS, EH11, EH15, EH21	0.024		BR7ES/130-136			
EH17 D/DS/B/BS, EH25 D/DS/B/BS	0.024		BR6HS/130-135			
EH30 V/VS, EH34 V/VS	0.024	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
EH36, EH41, EH72	0.024		BPR5ES/130-930			
<b>EX Series 4-Cycle OHC</b>						
EX13, EX17, EX21, EX27, EX27 Fuel Injection, EX30, EX35, EX40	0.024		BR6HS/130-135			
<b>TECUMSEH</b>						
<b>Horizontal 2-Stroke</b>						
AH520, AH600, HXL840, TCH200	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
TCH300	0.030	RCJ6Y/130-073	BPMR7A/130-898			
<b>Horizontal 4-Stroke</b>						
H20	0.030		BPMR7A/130-898			
H22, H25, HT30, HT35, HXL35, HH40, HH50, HH60, HH70, HMXL70, HH80, HHM80, HH100, HSSK60, HSSK70	0.030	J8C/130-093				
H30, H35, H40, H50, H60, H70, H80, HM70, HM80, HM90, HM100, HS40, HS50	0.030	RCJ8/130-091	BR4LM/130-916	SE-8JC/130-096	L6C/131-011	WS8E/130-112
HMSK70, HMSK80, HMSK90, HMSK100	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	
WR11E0/130-108						
OH120, OH140, OH160	0.030		BR6HS/130-135			
OH180, OH195EA, OHH50, OHH55, OHH60, OHM120, OHSK50, OHSK55, OHSK110, OHSK120	0.030		BR7ES/130-136			
<b>Vertical 2-Stroke</b>						
TC200	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
TC300	0.030		BPMR7A/130-898			
TVS840, TVXL840	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	
WR11E0/130-108						
AV520, AV600, TVS600	0.028		BR4LM/130-916			
<b>Vertical 4-Stroke</b>						
ECV100, ECV105, ECV110, ECV115, ECV120, LV148, LV195EA, LEV100, LEV115, LEV120, TV275, TVS90, TNT100, TNT120, TVS100, TVS105, TVS115, TVS120, TVXL105, TVXL115	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	
WR11E0/130-108						
LAV25, LAV30, LAV35, LAV40, LAV50, OVM120, TVM125, TVM140, TVM170, TVXL170, V40, V50, V60, V70, V80, VH40, VH50, VH60, VH70, VH80, VH100, VM70, VM80, VM100	0.030	J8C/130-093				
OHV100, OHV110, OHV115, OHV120, OHV125, OHV130, OHV135, OHV14, OHV145, OHV15, OHV155, OHV16, OHV165, OHV17, OV195EA, OV350EA, OV490EA, OVRM35, OVRM40, OVRM50, OVRM55, OVRM60, OVRM65, OVRM905, OVXL125	0.030		BR7ES/130-136			

\* Net Priced Item

## Spark Plug Application Chart



### GAS ENGINES [Cont.]

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>TECUMSEH (Cont.)</b> TVM195, TVM220, TVXL195, TVXL220, VLV40, VLV50, VLV55, VLV60, VLV65	0.030		BR4LM/130-916			
<b>Snow King 2-Stroke</b> HSK300, HSK600, HSK635, HSK840, HSK845, HSK850	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
HSK860, HSK870	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	WR11E0/130-108
<b>Snow King 4-Stroke</b> HSK30, HSK35, HSK40, HSSK40, HSK50, HSSK50, KSK60, LH195SP, LH318SA, OH318SA, HSK60, HMSK70, HSK70, HMSK80, HMSK85, HMSK90, HMSK100, HMSK105, HMSK110	0.030	RJ19LM/130-106	BR2LM/130-902			
OHSK70, OHSK130	0.030		BR7ES/130-136			
TH098SA, TH139SA, TH139SP	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
OHSK50, OHSK55, OH195SA, OHSK60, OHSK65, OH195SA, OHSK70, OH195SP, OHS75, OH318SA, OHSK80, OHSK90, OHSK100, OH318SA, OHSK110 (Spec. #223000 and higher), OHSK120 (Spec. #223000 and higher), OHSK130 (Spec. #223000 and higher)	0.030	RN4C/130-615				
OHSK110 (Spec. #222999 and lower), OHSK120 (Spec. #222999 and lower), OHSK130 (Spec. #222999 and lower)	0.030	L86C/130-085				
<b>WISCONSIN-ROBIN</b> <b>Horizontal Shaft</b> ECO2R	0.024	CJ6/130-098	BM7A/130-864			
EY18-3W, EY25W, EY27W, EY44W, W1-145, W1-185	0.024	L86C/130-085	B6HS/130-712			
EY21W	0.024	J8C/130-093	B6S/130-781			
W1-080, W1-150	0.024	L86C/130-085	BP6HS/130-272			



**Buy only what you need.**

**All spark plugs are sold individually.**  
Eliminate expensive inventory stock and order what  
you need, when you need it.



\* Net Priced Item

## Spark Plug Application Chart

### **T** TRIMMERS/BLOWERS

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>CRAFTSMAN/SEARS</b> <b>Blowers/Trimmers</b> Fuji 79691, 795451, 795453, 79623, 79624	0.030	L86C/130-085	B6HS/130-712			
79692, 795440, 795800, 795900	0.030	RCJ8/130-091	BMR6A/130-690	SE-8JC/130-096	L6C/131-011	WS8E/130-112
79510, 795420, 795430, 795490, 795510, 795340, 795520, 796131	0.030	CJ14/130-097	BM4A/130-708	SE-14JC/130-070		
<b>ECHO</b> <b>Trimmers/Brushcutters/Edgers</b> GT100, GT200i, GT200A, GT200B, GT200BE, GT200CE, GT200EZR, GT200R, GT201i, GT201R, GT201iEZR, GT230, GT231, GT251, GT251E, GT1000, GT140A, GT140B, GT160, GT160A, GT160AE, GTL140, GTL140A, PE200, PE201, PE230, PE231, PE260, PE261, PE310, PE311, SRM140DA, SRM200, SRM200AE, SRM200BE, SRM200CE, SRM200D, SRM200DA, SRM200DB, SRM202DA, SRM200FA, SRM210, SRM200E, SRM200AE, SRM210SB, SRM210i, SRM210U, SRM211, SRM211i, SRM211SB, SRM230, SRM230S, SRM230U, SRM231, SRM231U, SRM251E, SRM260, SRM260S, SRM260SB, SRM260U, SRM261, SRM261S, SRM261SB, SRM261T, SRM261U, SRM300, SRM300E, SRM300AE, SRM300AE/1, SRM302ADX, SRM310, SRM310S, SRM310U, SRM311, SRM311S, SRM311U, HC1000, HC1001, HC140, HC150, HC150i, HC151, HC151i, HC160, HC160A, HC161, HC180, HC181, HC200, HC201, HC230, HC231, HC233, HC234, HC260, HC200AE, HC210E, HC210AE, HCA261, HCR150, HCR151, SHC210, SHC211, SHC212, SHC260, SHC261	0.025	CJ6Y/130-077	BPM8Y/130-884		L7TC/131-003	WS7F/130-120

\* Net Priced Item

## Spark Plug Application Chart

### TRIMMERS/BLOWERS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>ECHO (Cont.)</b> <b>Trimmers/Brushcutters/Edgers (Cont.)</b> GT1100, GT201, GT201EZR, GT201R, GT2000, GT2000EZR, GT2000R, GT2000SB, GT2100, GT2101, GT2102, GT2103, GT2200, GT2400, PE2000, PE2400, PE2601, PE3100, SRM1500, SRM1500A, SRM1501, SRM2000, SRM211, SRM211SB, SRM211U, SRM260, SRM260S, SRM340, SRM400, SRM400U, SRM2100, SRM2101, SRM2100B, SRM2100SB, SRM2110, SRM2200, SRM2300, SRM2301, SRM2310, SRM2400, SRM2400SB, SRM2410, SRM2450, SRM2500, SRM2501, SRM2501S, SRM2502, SRM250E, SRM2510, SRM2601, SRM3000, SRM3001, SRM3010, SRM3100, SRM3100S, SRM3100S, SRM3110, SRM3400, SRM3800, SRM4600, SRM400BE, SRM400AE, SRM400BE, HC1500, HC1600, HC2000, HC2100, HC2400, SHC1700, SHC2100, SHC2400	0.024	CJ7Y/130-075	BPM7Y/130-785	SE-Y7C/130-146		WS7F/130-120
<b>Power Blowers</b> PB46LN, PB200, PB201, PB210, PB211, PB230LN, PB231LN, PB260i, PB260L, PB261i, PB261L, PB403H, PB403T, PB410, PB411, PB413H, PB413T, PB460LN, PB461LB, PB610, PB611, PB620, PB650, PB650H, PB650T, PB651H, PB651T, PB750H, PB750T, PB751H, PB751T	0.025	CJ6Y/130-077	BPM8Y/130-884		L7TC/131-003	WS7F/130-120
PB46HT, PB46LN, PB60HT, PB210E, PB230LN, PB260L, PB403, PB600, PB601, PB602, PB603, PB1000, PB2100, PB2400, PB4600, PB6000	0.024	CJ7Y/130-075	BPM7Y/130-785	SE-Y7C/130-146		WS7F/130-120
<b>GREEN MACHINE</b> <b>Blowers</b> 2600, 4600BP, 4600K, 4600LP, Blowers Xenoah	0.030	RCJ8/130-091	BMR6A/130-690			
3000HB	0.030	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
8000, 9000	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	WR11E0/130-108
<b>Trimmers/Edgers</b> 1900e Stick Edger, 1900EM, 500e Edger	0.030	RCJ8/130-091	BMR6A/130-690			
1800, 1930	0.030	DJ8J/130-071	BM6F/130-807	SE-J7D/130-153		HS8E/130-151
2000, 4000, 4500 3/8" Reach, 1700, 1730, 1900 1900E, 1930M, 1940M 2000, 2100, 2200, 2300 Series, 2400, 2400M3, 2500, 2600, 2600H, 2800, 2840, 3000, 3000B, 3000J, 3000M, 3000SS, 3040M, 3510, 3540, 4000, 4000B, 4000J, 4000M	0.030	RCJ8/130-091	BMR6A/130-690			

\* Net Priced Item

# Spark Plug Application Chart



## TRIMMERS/BLOWERS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>GREEN MACHINE (Cont.)</b>						
<b>Trimmers/Edgers (Cont.)</b>						
3000J, 4800	0.030		BM7A/130-864			
4000, 4500 1/2" Reach	0.030	L86C/130-085	B6HS/130-712			
1600, 2230	0.030	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
1940	0.030	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
2500LP, 2540LP	0.030	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
3000LP, 3800LP	0.030	CJ7Y/130-075	BPM7Y/130-785	SE-Y7C/130-146		WS7F/130-120
4000LP, 4500LP	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
<b>HOMELITE</b>						
<b>Blowers/Vacuums</b>						
BackPacker, Yard Broom, Vac Attack	0.028	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
BP250, BX90, HB100, 180, 180V, HB280, 380, 480, 680, HB390, 390V	0.025	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
11B-1B Ventilating Blower	0.030	J19LM/130-105	B2LM/130-777	SE-19J/130-211	GL4C/131-007	WR11E0/130-108
<b>Brushcutters/Trimmers</b>						
XL	0.025	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
XLBC-4, ST-400, XLBC-4	0.025		BM7A/130-864			
ZR Series (625, 725, 825, 830, 885), ST-160, ST-160A, ST-180, ST-175G, SX-135, 155	0.025	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
ST-80, ST-90, ST-100, ST-120, ST-150, ST-155, ST-175, DT-175BC, ST-385, ST-485	0.025	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
UT20000 Series, UT41002	0.028	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
<b>HUSQVARNA</b>						
<b>Blowers/Edgers/Hedge Trimmers/ Trimmers/Brushcutters</b>						
122HB, 18H, 21LCN	0.025	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
125BT, 225B, 225BX	0.020	RCJ8/130-091	BMR6A/130-690			
132HBV, 145BT/BF, 155BT, 165BT, 225HBV, LE326Ex, 225B, 225H, Mondo, Mondo Max, Mondo Mega, 122L, 123C, 223L, 225E, 225L, 225LD, 225RJ, 225R, 225RD, 232L, 232R, 235R, 240RBD, 240R, 245R, 245Rx, 250R, 265Rx, 323C, 323E, 323L, 323R, 324L, 325Cx, 326Ex, 326L, 326LD, 326Lx, 326Rx, 326Rjx, 326Sx	0.020/ .0250	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
140B, 25H, 26H	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
180BF, 226HD60S, 226HD75S, 226HS75S, 226HS99S	0.024		CMR7H/130-793			
LE309, LE359, LE389, LE389HD	0.030	J19LM/130-105	B2LM/130-777	SE-19J/130-211	GL4C/131-007	WR11E0/130-108
32LC, 32L	0.024	RCJ7Y/130-241	BPMR6A/130-815			

\* Net Priced Item



## Spark Plug Application Chart

### TRIMMERS/BLOWERS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>KAWASAKI</b>						
<b>Blowers/Edgers/Trimmers</b>						
KRB300A, KEL26A, KEL27A, KBL23A, KBL26A, KBL27A, KBL34A, KGT27A, KTR26AC, KTR27A, KHD600B, KHS750B, KHS1100B, KHT600D, KHT600S, KHT750D, KHT750S	0.030	RCJ7Y/130-241	BPMR6A/130-815			
KRB400A, KRB400B, KRB450BC, KRB650B, KRB700B, KRB750B, KHS750BC, KHT600SC, KHT750SC	0.026	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
KHD600A, KHS750A, KHS750AC, KHS1100A	0.025		BPMR4A/130-716			
<b>MAKITA</b>						
<b>Brushcutters/Trimmers/Blowers/Edgers</b>						
RBC252, RST250, RBC221, RBC230, RBC251, RBC253, RBC25A, RBL250, RBE250	0.025		BM7A/130-864			
RBC310, RBC260, RBC261, RBC311, RBL500	0.025	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
DBC300, DST300, DST301	0.020	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
<b>MARUYAMA</b>						
<b>Brushcutter/Blowers/Edgers/Trimmers</b>						
BC200, BC200C, BC201, BC201C, BC2320, BC2620, BC2030, BC3020, BC260, BC260C, BC2600, BC2800, BC3200, BC4200H, BC260H BC320, BC320H, BC402M, BC420H, BC480M, BC500H, BC2300, BCL2250, BCL2250C, BCL2550, MC2330, MC2610, MC2620, MC260, MC260C, MC260D, MC60E, MC260S, MC260T, MC261, MC321, MC2300, MC2610, MC2310, MC3210, ML23, ML23S, HT159, HT159L, HT220, HT230, HT230D, HT230L, HT2300, HT2300D, HT2300L, HT242, HT242L, HT260D, ML23H, EHT2300, EHT2600	0.024	RCJ8Y/130-079	BPM7Y/130-785	SE-Y7C/130-146	L6RTC/131-051	
BCGX22, BCGX31	0.025		CR5HSB/130-340			
BL230, BL400/BL4000, BL471, BL480/BL4800	0.024	CJ6/130-038	BM7A/130-864			

\* Net Priced Item

# Spark Plug Application Chart


**TRIMMERS/BLOWERS** [Cont.]

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>MCCULLOCH</b>						
<b>Blowers/Trimmers</b>						
Eager Beaver (I, II, III, IV, SX, Super, SL, 280, 282, 285, 287, 325, 327, Blowers), Power Blower, Pro Steam Blower, Silver Eagle (III Blower, IV Blower, 28, 32), Super Air Stream III, Super Air Stream, PB250, Mac )GHT17, 19, 22, 65, 80, 99, 281, 2815, 2816, 2817, 2825, 2827, 3225, 3227, 3227HD, SL, SX), Pro Mac (I, II, III, IV, Super, HD), Pro Scalper (I, II, 28S, 32HDS, Super Mac (80, 85, S, SL, SX), Titan (GHT24, GHT30, GPO22), Roadrunner (I, II, III), Silver Eagle 28 and 32	0.025	DJ8J/130-071	BM6F/130-807	SE-J7D/130-153		HS8E/130-151
Mac (3516, 3818), Titan (2000, 2030, 2100, 2250, 2310, 2360, GLE2380, 2500, 2560AV, 25810-GLE, GLE2580AV, 3000, 3900)	0.025	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
<b>POULAN PRO</b>						
<b>Blowers/Trimmers</b>						
400, PP036, PP136	0.030	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
420, 442, PP200	0.025	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
422, 432, PP135, P22, PP112, PP115, PP175, PP185, PP195	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
BVM200	0.030	RCJ7Y/130-241	BPMR6A/130-815			
PP111, PP114, PP117, PP165	0.030		BM4A/130-708			
<b>RED MAX</b>						
<b>Blowers/Trimmers</b>						
HB260, BC340DL, BC430DWM, BC440DWM	0.025	RCJ7Y/130-241	BPMR6A/130-815			
EB430, EB440, CHT230, HT230	0.025	CJ6/130-098	BMR7A/130-864			
EBA430, EBA440	0.025	J8C/130-093				
BC220DL, BC260DL, BL220DL, BT17, BT171, BT220, BT221	0.025	RCJ8/130-091	BMR6A/130-690			
<b>RYOBI</b>						
<b>Blowers/Edgers</b>						
280r, 310BvR, 310r, 410r, 700r, 704r, 710r, 720Er, 720r, 740r, 750r, 760r, 765r, 766r, 767r, 768r, 770rEB, 780r, 855r, 865r	0.030	DJ8J/130-071	BM6F/130-807	SE-J7D/130-153		HS8E/130-151
725r, 725Er, 750r, 768r, 775r, 780r, 790Pr, 790r, 920Er, 920r, 925r, 960r, 970r, 975r, 990r	0.030	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
1075r, 1079r, 1090r, 2065r, 2085r, 825r, 875r, 890r, Pro-4-Mor, 510r	0.030	RDZ19H/130-109				
2075r, 2075rc, 2079r, 2090r, 2090RC	0.030	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
RD260, RD330, RD420	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6C/131-011	WS8E/130-112

\* Net Priced Item

## Spark Plug Application Chart

### TRIMMERS/BLOWERS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>SHINDAIWA</b>						
<b>Blowers/Trimmers/Edgers</b>						
EB45, EB480, EB500, EB501, EB240, EB240S, B40, B45, B450, BP25, BP35, C20, C25, C27, C35, C230, C250, C350, F230, RC45, T18, T20, 22T, 22F, T25, T230, T231T250, T350, LT-20, 22-DH, AH230, AH231, HT-20, HT-230, HT-231, DH-230, DH-231, LE230, LE-231, LE-250, P230, P231, F18, F20, F21, 22F	0.024	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
EB630	0.024	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
EB854, EB854RT, EB254, EB344, C254, C344, T254, T344, AH254, AHS254, DH254-24, SH254-30, HT254-30, HT254-40, LE254, PS344	0.024		CMR5H/130-694			
C242, T242, LE242	0.024	RCJ7Y/130-241	BPMR6A/130-815			
C260, C270, T27, T260, T261, T270, T272X, LE260, LE261	0.025	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
<b>STIHL</b>						
<b>Trimmers</b>						
FR38, FS36, FS40, FS44, FS44J, FS44R, FS50, FS51, FS56AVRE, FS60, FS61, FS65, FS90	0.030	RCJ8/130-091	BMR6A/130-690			
FS20, FS48, FS52, FS62, FS45, FS45C, FS46, FS46C, FS55R, FS55RC, FS55, FS75, FS80R, FS85, FS81, FS86, FS106FS120, FS120R, FS150, FS151, FS160, FS180, FS280K, FS360AVEZ, FS200, FS200AV, FS200AVE, FS200R, FS202, FS202AV, FS220, FS420, FS300, FS350, FS400, FS450, FS480, FS500, FS550, FS250, FS250R, FS401, FS410AVE	0.030	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
FS56, FS130, FS310	0.020		CMR6H/130-355			
FS110, FS100RX, FS110R, FS130R	0.028		CMR5H/130-694			
FS72, FS74AVRE, FS76AVE, FS76AVRE, FS108, FR106, FS401AVE	0.030	RCJ8/130-091	BMR6A/130-690			
FS353, FS353AV	0.028		BPR6HS/130-847			
<b>Blowers/Sprayers/Edgers/ Hedge Trimmers</b>						
BG17, SG17, BG45, BG46, BG55, SH55, BG060, BG061, BG65, BG85, SH85, BG75, BR45, BR46, BR320, BR320L, BR340, BR340L, BR380, BR400, BR420, BR420CBT45, BT120, BT121, FC55, FC75, FC85, FH75, H151, HS202, HS60, HS61, HS242, HL45, HL75, HL75K, HS45, HS75, HS80, HS85	0.030	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
BG56C, BG66, BG86, BG86C, SH56, SH86, BR500, BR550, BR600, FC56, HT130, HT131	0.028		CMR6H/130-355			
BG72, BR106, HS72, HS74, HS76	0.020	RCJ7Y/130-241	BPMR6A/130-815			
FC44, FC72	0.030	RCJ8/130-091	BMR6A/130-690			
FC73, FC83, HL73, HT70, HT75, HT73	0.025		CMR7A/130-348			
FC90, FC95, FC100, FC110, HL90, HL100, HS81R, HS86	0.020		CMR5H/130-694			

\* Net Priced Item

# Spark Plug Application Chart


**TRIMMERS/BLOWERS** (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>TANAKA</b>						
<b>Blowers/Brushcutters/Edgers</b>						
TBL-500, TBL-505, TBL-2400, TBL-4600, THB-300, TBC-300, TBC-322, TNC-355, TBC-3010, TLE-500, TLE-550	0.024		BM7A/130-864			
TBL-2500, TBL-2510, THB-2510, AST-7000, TBC-420PF, TBC-430PF, TBC-500, TPE-250	0.025	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
THB-2100, TPE-2100, TPE-2410	0.024	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
QUM-2, QUM-2N, SUM-3, SUM-301, SUM-321, TBC-218, TBC-220, TBC-240, TBC-265, TBC-422C, TBC-425, TBC-501, TBC-4110, TST-218	0.024	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
TBC-270PF, TPE-270PF, TPE-2510	0.024	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146		WS7F/130-120
<b>Trimmers</b>						
PHT-15, PHT-25, THT-23, THT-162, THT-200, THT-230, THT-232, THT-262, TBC-4010	0.024	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
THT-240, THT-2100, THT-2120, THT-2510, THT-2520, THT-2530, THT-2540, AST-210, AST-5000, AST-7000, TBC-220, TBC-250TBC-420PF, TBC-430PF, TBC-2211, TBC-2510, TBC-4000, TBC-4500, TBC-5000, TBC-2510	0.025	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
TPH-2540, TBC-270PF	0.024	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146		WS7F/130-120
TBC-200	0.025	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
TBC-355	0.024		BM7A/130-864			
TBC-2100, TBC-2110, TBC-2400, TBC-2410, TBC-2800	0.024	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
<b>TORO</b>						
<b>Trimmers</b>						
51930, 51932, 51934	0.028		CMR7A/130-348			
51620, 51638, 51652, 51653, 51660, 51675, TC1000, TC2000, TC3100, TC3500, TC5000	0.025	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
<b>WEEDEATER</b>						
<b>Blowers/Trimmers</b>						
920, 925, 940, 960, 1920, 1925, 1960, 599, 609, 698, XR200	0.025	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	WS8F/130-116
BV165, GBI 20, GBI 22, GBI 30, LT7000, LT7500	0.025	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
1000	0.025	L86C/130-085	B6HS/130-712			
1400, 1500, 1600, 1700, 1900, 4000, 5000, GTI 15, GTI 16, GTI 17, GTI 18, GTI 19, GTI 52, HP22, HP28, HP30, SST45, TBC57, XR20, XR30, XR50, XR70, XR75, XR80, XR90, XR95, XR100, XR105, XR125, XT20, XT30, XT40, XT50, XT85, XT90, XT100, XT125	0.030	CJ14/130-097	BM4A/130-708	SE-14JC/130-070		

\* Net Priced Item

## Spark Plug Application Chart

### CHAINSAWS/CUT-OFF SAWS

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>CRAFTSMAN/SEARS</b>						
<b>Chainsaws</b>						
1.9S, 2.0, 2.1A, 271-1.8, 271-2.7A/VL, 3.6, 3400, 3401, 3402, 3408, 3411, 3412, 3415, 3416, 3418, 3425, 3455, 3460, 3461, 3465, 34663476, 3481, 34071, 3409435082, 35091, 35093, 34094, 35096, 35201, 35202, 35177, 35187, 3119735203, 35205, 35206, 352030, 352060, 352070, 352090, 35207, 35209, 35232, 35211, 35215, 352231, 352351, 35265C, 35238, 35251, 35255, 35251, 35256, 35263, 35266, 35267, 3537135363, 35366, 35367, 35369, 35373C, 35377C, 35481, 35483, 35487, 35505, 35506, 35512, 35514, 35515, 35516, 36096, 36212, 36235, 357120, 357160, 358810, 358840, 35883, 35887, 35889, 358860, 36212, 59716, 59741, 59816, 59886, 714.3A/VL	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
3.7, 3.7A, 3.7PS, 35158, 35147, 35148, 35171, 35372, 35373, 35375, 35376, 35607, 35628, 35633, 35718, 35886, 35904, Beaver 1.9	0.030	CJ6/130-098	BM7A/130-864		L7TC/131-003	
35269, 35365, 35505	0.025	DJ8J/130-071	BM6F/130-807	SE-J8D/130-138		
35484, 35608, 35609, 35885, 358356, 35881, 35889, 358850	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
59820, 59918	0.030	RCJ7Y/130-241	BPMR6A/130-815			
<b>DOLMAR</b>						
<b>Cut-Off Saws</b>						
PC6412, PC6414, PC6430, PC6435, PC6530, PC6535, PC7312, PC7314, PC7330, PC7335, PB7430, PC7435, PC8114, PC8116, PC8135, PC8140, PC8240	0.020	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WR6F/130-124
<b>Chainsaws</b>						
103, 105, 108, PS3300TH	0.030	RCJ8/130-091	BMR6A/130-690			
109, 110, 110i, 111, 111i, 112, 113, 114, 115, 115i, 116, 116Si, 117, 118, 119, 120, 120 SUPER, 120Si, 122, 123, 128 KMS4 Rotary, 133, 133 Super, 143, 144, 152, 153, 166, 310, PS-460, PS-510, PS-5100S, PS-540, PS-6000i, PS-6400, PS-6800i, PS-7300, PS-7900, PS-9000, PS-9010, PS-9010i, PS34, PS342	0.020	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WR6F/130-124
309, 343	0.020	RCJ7Y/130-241	BPMR6A/130-815			
<b>ECHO</b>						
<b>Cut-Off Saws</b>						
CSG-670, CSG-6700	0.025	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
CSG-680	0.025	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146		WS7F/130-120

\* Net Priced Item

# Spark Plug Application Chart



## CHAINSAWS/CUT-OFF SAWS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>ECHO (Cont.) Chainsaws</b>						
CS-300, CS-300-14, CS-301, CS-341, CS-346, CS-520, CS-6700, QV-6700	0.025	CJ6Y/130-077	BPM8Y/130-884		L7TC/131-003	WS7F/130-120
CS-305, CS-330T, CS-340, CS-345, CS-360T, CS-440, CS-520, 3900, 4400, 4500, 4600, 5000, 510EVL, 5500, 660EVL, 6700, 702EVL, 702VL, 750EVL, 8000	0.025	RCJ6Y/130-073	BPMR8Y/130-115		L7RTC/131-023	WR6F/130-124
CS-3000, CS-3400, CS-3540, CS-4400, CS-5000, CS-510, CS-520, CS-8000, QV-670, QV-675, QV-6750, QV8000, QV-8050	0.025	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146		WS7F/130-120
100, 280EP, 300EVL, 301, 302, 302S, 304, 315, 330, 351VL, 451VL, 452VL, 601, 601S, 601SVL, 602EVL, 60S, 650EVL, 701SVL, 701VL, 801, 802, 80Z, S290	0.025	RCJ8/130-091	BMR6A/130-690			
1001VL, 2800, 2900, 290EVL, 290EVLP, 3000, 330EVL, 330EVLP, 3400, 3450, 4000, 4000EVLP, 410EVL, 440EVL, 440EVLP, 410EVL, 440EVL, 440EVLP, 510EVL, 550EVL, 601EVL, 602VL, 610EVL, 620VL, 650EVLP, 660EVLP, 660VL, 750EVLP, 852EVL, 900EVL	0.025	RCJ7Y/130-241	BPMR6A/130-815			
280E, 290EVL, 300EVL, 400EVL, 500EVL	0.025	RCJ8Y/130-079	BPM7Y/130-785	SE-Y7C/130-146	L6RTC/131-051	
<b>GREEN MACHINE Chainsaws</b>						
20	0.030	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
30, 33, 38	0.030	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
7100, 7200, 7400	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
7600, 7700	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
<b>HOMELITE Chainsaws</b>						
1010, 1050, 1130G, 2100 Super, 2100S, 3100G, 35SL, 650, 750, 945, 955, Big Red SXL, Old Blue SXL, DM-20 Multi-Purpose, DM-50 Multi-Purpose, MP38, MP88 Multi-Purpose, Super 1050, Super 1130G, Super XL, Super XL-925, Super XL-AO, VI123, XL123, XL660F, XL923, XL923A, XL924A, XL925, V1-944, V1-955, XL98D	0.025		BM7A/130-864		L7TC/131-003	
Multi-Purpose 150, 190, 240, Super 240, Super-2, V1-Super-2, XL, XL-2	0.025	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
180, 192, 200, 245HG, SL, 252, 540, CS-40, DM-40, DM-54 Multi-Purpose, LX30, Little Red XL	0.025	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		

\* Net Priced Item

# Spark Plug Application Chart



## CHAINSaws/CUT-OFF Saws [Cont.]

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>HOMELITE (Cont.)</b>						
250, 290, 300, 340, 8800, z2240b, z3850b, z3330, z3350	0.025	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	W-S7F/130-120
C72, Super Wiz 55, Super Wiz 66, Super Wiz 80	0.025	J8C/130-093	B6S/130-781	SE-8J/130-096		
XL-12, XL100A	0.025	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
<b>HUSQVARNA</b>						
<b>Cut-Off Saws</b>						
268K, 272K, 371K, 375K, 3120K	0.020	RCJ8Y/130-079	BPMR6A/130-815		L6RTC/131-051	
K750, K760, K950, K960, K970, K1250, K1260	0.020	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	W-SR6F/130-124
<b>Chainsaws</b>						
136, 141, 20PS, 261, 2101XP, 2405, 23 Compact, 242XP, 244, 254XPG, 260CD, 254XP, 257, 260, 262XPG, 263CD, 266SG, 266XP, 262XP, 266SE, 272XPG, 280G, 281, 268, 26RCL, 32R, 32RCL, 32, 165RX, 272XP, 281XP, 285CD, 185CD, 1100CD, 2100CD, 3130, 288XP, 3120XP, 33, 34, 335XP, 335XPT, 380S, 480CD, 280S, 280CD, 340, 340SE, 340SG, 380CD, 345, 346XP, 350, 351, 353, 357XP, 359, 36, 365, 371XPG, 394XPG, 371XP, 372XP, 385XP, 394XP, 395XP, 40, 41, 42, 44, 444, 444SE, 444SG, 444FE, 444FG, 480K, 45, 49, 50, 65, 51, 55, 55 Rancher, 61 66, 77, A77, B77, L77, S77, HUSKY 246, HUSKY 35VR, Husky 36R, Husky 38, Husky 39R, Husky A65, Husky B65	0.020	RCJ7Y/130-241	BPMR7A/130-898		L7RTC/131-023	W-SR6F/130-124
140, 140S, 154, 160CD, 160SG, 162FE, 162FG, 162SE, 162SG, 163S, 163SE, 165, 165R, 180S, 1R, 16, 18, 22R, 22RL, 24, 25RL	0.020	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
2100CDW, 35, 37, Husky 22, Husky 23, Compact 35, Compact 37	0.020		BM7A/130-864		L7TC/131-003	
A100, G90, SM150	0.020	L86C/130-085	B6HS/130-712			
<b>JOHN DEERE</b>						
<b>Chainsaws</b>						
12, 14, 15, 17, 18, 19, 23, 350CS, 61, 8, 9, 81, 82, 91	0.030		BM7A/130-864		L7TC/131-003	
200CS, 230CS, 550CS, 820, 840	0.030	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	W-S7F/130-120
25EV, 46EV, 51SV, 55EV, 65EV, 300CS, 55V, 60V, 65SV, 66SV, 450V, 800V, 70V, 72, 80EV, R70EV, S80, S82	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
28, 30, 35EV, 40V, 50, 50V	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6C/131-011	W-S8E/130-112

\* Net Priced Item

# Spark Plug Application Chart



## CHAINSAWS/CUT-OFF SAWS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>JONSERED</b>						
<b>Chainsaws</b>						
111S, 435, 450, 2036, 2040, 2041 Turbo, 2045, 2050, 2051 TURBO, 2051, 2054, 2055 Turbo, 2055 Cat, 2063, 2065, 2071 Turbo, 2071W, 2077, 2083 Turbo, 2094, 2095 Turbo, 451EV, 521EV, 525, 535, 45ES, 49SP, 52ES, 66E, 590, 621, 625 II, 630 Super II, 630S, 670 Champ, 801, 830, 910D, 66ES, 70E, 90W, 910E, 920, 930S, BadNSaw Mill 6000+, HP36 Power Pruner, M50, M80, M110, M52, M510SP, M60, M62, M601, M621, M75, M751, Mini Sawmill 600+, MK70, MK80, RS45, Pro 35, Super III	0.030	CJ8Y/130-072	BPM6A/130-831		L6TC/131-027	
410, 420, 490, 510, 510M, 520SP	0.030	DJ7Y/130-076	BPM6F/130-761	SE-J7D/130-153		
365, L1L-J, M36, M361, M361AV	0.030	J8C/130-093	B6S/130-781	SE-8J/130-096		
820, 840	0.030	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
<b>MAKITA</b>						
<b>Cut-Off Saws</b>						
DPC6400, DPC6401, DPC6410, DPC6411, DPC7300, DPC7301, DPC7310, DPC7311, PDC7321, PDC7331, DPC8112, DPC8132, EK7301	0.020	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	W-R6F/130-124
<b>Chainsaws</b>						
DCS-330S, DCS-340, DCS-341, DCS-390, DCS-400, DCS-401	0.025	RCJ8Y/130-079	BPMR6A/130-815		L6RTC/131-051	
DCS-430, DCS-431, DCS-5200i, DCS-520i, DCS-6800iFL/FW, DCS-9000FL/FW, DCS342, DCS391, DPC-7000, DPC-7001, DPC-9500, DPC-9501, DPC6200, DPC6201, DPC7003, DPC7301	0.025	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WR6F/130-124
<b>MCCULLOCH</b>						
<b>Chainsaws</b>						
1.9, 2.3, Titan 560, Titan 620	0.025	RCJ7Y/130-241	BPMR6A/130-815			
10-10, 10-10A, 10-10L, 3-10, 3-10E, 895, Double Eagle (50, 80) Eager Beaver (10, 12, 14, 16, 2.0, 2.1, 2.3, 3.4, 3.7) Mac (100, 110), Pro Mac (40, 4700AV, 5000, 510, 555, 570, 5700AV, 5720, 605, 610, 650, 690, 700) S10-10, S10-10LA 795, S10-10LA 795L, S10-10LA 797, S10-10LA S797, S2-10A	0.025	DJ8J/130-071	BM6F/130-807	SE-J8D/130-138		
250, 550, 650, 660, 940, S250, S550	0.025	J8C/130-093				

\* Net Priced Item



## Spark Plug Application Chart



### CHAINSAWS/CUT-OFF SAWS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>MCCULLOCH (Cont.)</b> 5-10A, 5-10G, 6-10, 6-10A, 7-10A, CP-125, CP-125S, CP-70, CP-70L, G-70, LG-6, MAC 10 SERIES, 4-10, 5-10, PM-60, PRO MAC (3800, 800, 8200, 850) S6-10A, SP105, AP125C, SP40, SP60, SP80, SP81	0.025	DJ6J/130-101				
Eager Beaver (2000, 2100AV, Super 2300AV) Mac (3200 series, 3500AV series, 3800AV series) Mac Cat (16, 18) MS1432, MS1635, MS1635AV, MS1838AV, Pro Mac (2500, 3205AV-14, 3505AV-16, 380)	0.025	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
<b>OLYMPYK</b> All Models	0.030	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146	L7TC/131-003	WS7F/130-120
<b>PARTNER</b> <b>Cut-Off Saws</b> K650, K700 Active I, II and III, K850, K1200, K500	0.020	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146	L7TC/131-003	WS7F/130-120
<b>Chainsaws</b> 1610, 1611, 1612, 1613, 1614, 1614C, 1616, 1616C, 1705, 1712, 933, 944, 946, 947, Partner Mini III, Partner Mini IV	0.030	DJ7J/130-099	BM6F/130-807	SE-J7D/130-153		
1629, 1630, 1631, 1644, 1645, 1660, 1661, 1690	0.030	J8C/130-093				
1632, 1632C, 1646, 1646C, 1647C, 1655, 1655B, 2055, 2055B	0.030	CJ6/130-098	BM7A/130-864			
F55, F55A, F65, K-12, S65	0.030	L86C/130-085	BP6HS/130-272			
K-20, K-40, R-16, R-17, R-30, TS	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	
Mini-P, Mini-P11, Mini-PA, P55, P70, P7000, P85, R-20, R-20T, R-40T, R-44T, R-417T, R-420, R-420T, R-421T, R-435, R-517, R-517T, R-85	0.030	CJ6/130-098	BM7A/130-864		L7TC/131-003	
<b>POULAN</b> <b>Chainsaws</b> 100, 20, 20D, 245A, 25, 252A, 25DA, 25SN, 306, 306A, 306SA, 361, 5200CVA, 71A, 72, 76, 92 Micro MZ5, Micro XXV, Model XX, S25, S25AV, S68, S72, Super XXV	0.025	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6TC/131-027	

\* Net Priced Item

# Spark Plug Application Chart



## CHAINSAWS/CUT-OFF SAWS (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>POULAN (Cont.)</b>						
180, 1800, 1950, 200, 2000, 205, 2050, 2100, 2150, 2175, 2250, 2300, 2350, 2375, 2400, 2450, 2500, 2550, 2600, 2750, 2900, 3050, 355, 405, 415, 4200CVA, 6000CVA, KS412, P3314, P3314WS, P3416, P4018, P4018WT, PP225, PP190 Arborist, PP210, PP230, PP235, PP236, PP255, PP260, PP295, PP310, PP315, PP405, PP415, PP425, PP445, PP455, PP475, PP505, PP525, PP655, PPS23 Arbor Pro, PPS25DA, S23, S6000, Wild Thing 2175, Wild Thing 2375	0.025	CJ7Y/130-075	BPM7A/130-880	SE-Y7C/130-146	L7TC/131-003	WS7F/130-120
3400, 3700, 375, 3800, 4000, PP325, PP375, PP395	0.025	CJ8Y/130-072	BPM4A/130-789		L6TC/131-027	
3500, 3600, 3750, Bad Boy 3750, PP365, PP380	0.025	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	WS7F/130-120
4400, 4900, 5400, 6900, 7700, 8500	0.025	CJ6/130-098	BMR7A/130-864			
53A, 54, S33	0.025	J8C/130-093	B6S/130-781	SE-8J/130-096		
<b>STIHL</b>						
<b>Cut-Off Saws</b>						
TS350S, TS360, TS360AVE, TS400, TS410, TS420, TS460, TS480, TS50, TS510AVE, TS760AVE	0.020	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
<b>Chainsaws</b>						
06, 07, 07S, 08, 08H	0.020		BP6HS/130-272			
All other Stihl models	0.020	RCJ6Y/130-073	BPMR7A/130-898		L6RTC/131-051	WSR6F/130-124
<b>TANAKA</b>						
<b>Chainsaws</b>						
ECS-290, ECS-300, ECS307, ECS-320, ECS-330, ECS-350, ECS-351, ECS3301, ECS-351, ECS-3301, ECS3351, ECS-35, ECS-35B, ECS-35E, ECS3500B, ECS-355, ECS-356, ECS-357, ECS-370	0.030	CJ8/130-094	BM6A/130-799	SE-8JC/130-096	L6C/131-011	WS8E/130-112
ECS-405, ECS-415, ECS-505, ECS506, ECS650, ECS-655, ECV-4501, ES-650/20, ES650/24	0.030	CJ8Y/130-072	BPM4A		L6TC/131-027	
EBC-1, ECS-3, ECS-5	0.030		B6S/130-781			
ECV-4501 2.5HP, ECV5601 2HP	0.024	CJ6Y/130-077	BPM7A/130-880		L7TC/131-003	
<b>WACKER</b>						
<b>Cut-Off Saws</b>						
BTS930, BS930L3, BS935, BTS935L3, BTS1030, BTS1030L3, BTS1030L3, BTS1035, BTS1035L3, BTS1140L3	0.020	RCJ6Y/130-073	BPMR7A/130-898		LRTC/131-023	WSR6F/130-124

\* Net Priced Item

## Spark Plug Application Chart



### GOLF CARTS

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
<b>CLUB CAR</b>						
1500 with Honda engines	0.020	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	WR6DC
1200 and 1200SE with Kawasaki engines, Café Express (2003), Carryall 272 (2000-2003), Carryall II Plus (1992-2000), Carryall Turf 2 XRT (2003), Carryall Turf II (1992-2000), Carryall Turf VI (2003), Carryall VI/XL (1992-2000), Limo/XL (1992-2000), Resort Villager/XL (1992-2000), Transporter/XL (1992-2003), Transsender/XL (1992-2000), Villager Series(2003), XRT (2000), Carryall Turf I, II (1992-2003), DS gasoline (1992-2003), Fairway Villager (1992-2000), Tourall (1992-2000) and Precedent (2005-2006)	0.028	RN11YC4/130-595	BPR5ES/130-930		F5RTC/131-043	WR7DC
<b>COLUMBIA PAR CAR</b>						
With Briggs & Stratton 9 HP Vanguard engines	0.030	RC12YC/130-526	BKR5E/130-119	SE-12RCY/130-191		FR8DC
Golf carts	0.030	RL95YC/130-107	BPR4HS/130-942			
<b>CUSHMAN</b>						
Hollister 1985 and newer	0.030	RV15YC4/130-081	UR4/130-740			
Hollister 1984 and older	0.030	RF14YC	WR5			
Trackster	0.030	J4C	B7S			
<b>E-Z-GO</b>						
(1/2" reach), Shuttles, Workhorse	0.025	L92YC	BP5HS/130-227			W8BC
6 X 1500	0.025	RS14YC/130-559	TR5/130-757			
ST-480	0.030	RC12YC/130-526	BKR5E/130-119	SE-12RCY/130-191		FR8DC
1200G	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	WR6DC
6 X 804, 6 X 810, 6 X 875, 875, 875A, 875P, Clay Car, Freedom LE, Freedom SE, MG5 (1997-1998), PC952, PC954, PC956, ST Sport, ST Sport 2+2, ST-350, TXT Series and 4x4	0.030	RN11YC4/130-595	BPR5ES/130-930		F5RTC/131-043	WR8DC
<b>HARLEY DAVIDSON</b>						
Model D 3/4" reach	0.040	RN14YC	BP4ES/130-223			
<b>YAMAHA</b>						
G 1-A (1979-1982), G 3A (1986)	0.024	RL95YC/130-107	BP5HS/130-227			W8BC
G 1-AM (1983-1986)	0.024	L87YC	BP6HS/130-272			W7BC
G 2A (1985-1988)	0.028	N5C	B5ES/130-215			W8C
G 2AD (1989), G 5A (1990-1992), G 8A (1990-1994), G 9A (1991-1994), G11A (1993-1994) and G14A (1996)	0.028	RN5C	BR4ES/130-264			
G14AM (1995), G14AP (1996), G15A (1999), G16A (1996-1997), G20A (2001-2002), G21A (2001-2002), G-Max 4 Stroke (2003), G-Max 48V (2003) and U-Max Utility (2003)	0.028		BPR2ES/130-934			

\* Net Priced Item