

Spark Plug Application Chart

GAS ENGINES

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
BRIGGS & STRATTON						
Fource	0.030	RDJ7Y/130-137				
Intek — single and twin cylinder OHV						
Vanguard — liquid cooled three cylinders, single cylinder OHV engines and 31 HP OHV V-twin	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
Single cylinder OHV engines — 97700 series, 99700 series, 197700 series, 28E700 series, 287700 series, 28N700 series, 28U700 series, 28W700						
Vanguard V-twin OHV (27 HP thru 32 HP)	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
Vanguard — V-twin OHV (12.5 HP thru 23 HP) 19A400-19G400 series, 93400 series (with top tank)	0.030	RC14YC/130-530	FR5/130-839			
Opposed twin cylinder "L" head, single cylinder "L" head	0.030	J19LM/130-105	BR2LM/130-902	SE-19J/130-211	G14C/131-007	WR11E0/130-108
625e, 675ex, 725ex series, 625-675 series and Quantum 7.5-6.75 gross HP engines	0.020					
HONDA						
GC135, GC160, GC190	0.030	RN11YC4/130-595	BPR6ES/130-823		F6RTC/131-039	
GC160A, GC190A, GS190A, GSV190A	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
GX22, GX31, GXH50, GXH50U, GX50, GX100U	0.025		CR5HSB/130-340			
GX25, GX25N, GX25NT, GX25T, GX35, GX35T, GX35NT	0.028		CMR5H/130-694			
G30, G35, G40, G41, G42, G80, GS65, GV35	0.028		BR6HS/130-135			
G65, G80	0.030	L86C/130-085				
G100	0.030	CJ14/130-097	BMR4A/130-756			
GV100	0.024	CJ14/130-097	BMR4A/130-756			
G150 (with Mag), G200, G300, G400	0.030		BR4HS/130-724			
GV150 2029059> (CDI), GV400	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
GV150 2029059 > (mag)	0.030	RCJ8/130-079		SE-8JC/130-096	L6C/131-011	WS8E/130-112
GV200, GV400	0.025		BMR6A/130-690			
G400	0.030	RL95YC/130-107	BR4HS/130-724			
GX100, GX110, GX120, GX140, GX160, GX200, GX240, GX240, GX270, GX340, GX390, GX610, GX620, GX670 (to 1999)	0.030	RN11YC4/130-595	BPR6ES/130-823		F6RTC/131-039	
GXV110	0.028	RN11YC4/130-595	BR4HS/130-724		F6RTC/131-039	
GXV120, GXV140, GXV160, GXV270, GXV340, GXV390, GXV520, GXV530	0.028		BPR5ES/130-930			
GX630, GX660, GX690, GXV630	0.030		ZFR5F/130-276			
GX670 (from 2000), GXV610, GXV620, GXV670	0.028		ZGR5A/130-835			
GCV135, GCV135A, GCV160, GCV160A, GCV160E, GCV190, GCV190A, GCV520U	0.030	RN11YC4/130-595	BPR6ES/130-823		F6RTC/131-039	
GXV50, GXV50U, GXV57U	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
GCV530, GCV530U	0.030	RN11YC4/130-595	BPR5ES/130-930		F6RTC/131-039	

* Net Priced Item

Spark Plug Application Chart

GAS ENGINES (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
KAWASAKI						
FA76D (from 1983)	0.028	CJ8/130-094				WS8E/130-112
FA76D (to 1982), KT12, KT15, KT18, KT28	0.024	CJ8/130-094				WS8E/130-112
FA130D, FA210D, FD501D, FD501V (to 1998), FD590V	0.025	RCJ8/130-091	BMR6A/130-690	SE-8JC/130-096	L6C/131-011	WS8E/130-112
FE120D, FE170D, FE250D, FE290D, FE350D, FE400D, FH741D, FH770D, FC150V, FC180V, FC290V, FJ180V, FC401V, FJ400D, FC420V, FC540V	0.028	RN11YC4/130-595	BPR5ES/130-930		F6RTC/131-039	WR8DC/130-154
FD620V, FD661D, FB460V, TF22	0.024		BMR4A/130-756			
FD440V, FD501V (From 2002), FD611V						
FD661V, FA210V, TG28	0.025	RCJ8/130-091	BMR6A/130-690	SE-8JC/130-096	L6C/131-011	WS8E/130-112
FD501V (1999-2001), FD680V, FD731V	0.028		BPR4ES/130-938			
FD601V, FD641V, FD671V, FD711D, FD750D, FD791D	0.025		BPR2ES/130-934			
FH381V, FH430V, FH451V, FH500V, FH531V, FH541V, FH580V, FH411V, FH480V, TH26, TEX45, TH23	0.028	RCJ8Y/130-079	BPMR4A/130-716	SE-8JC/130-096	L6C/131-011	WS8E/130-112
FH601D, FH601V, FH641D, FH641V, FH680D, FH680V, FH721D, FH721V	0.028		BPR4ES/130-938			
FR541, FR600V, FR691V, FR730V	0.028		BPR4ES/130-938			
FS481V, FS541V, FS651V, FS691V, FS730V	0.028		BPR4ES/130-938			
FX481V, FX541V, FX600V, FX651V, FX691V, FX730V, FX801V, FX850V	0.028		BPR4ES/130-938			
FX921V, FXT00V	0.028	RN11YC4/130-595	BPR5ES/130-930		F6RTC/131-039	WR8DC/130-154
FJ100D	0.028		BR6HS/130-135			
KF24, KF52, KF53, KF53A, KT43	0.024	L86C/130-085				
KF34, KF68, KF81, KT15J, KT18J, KT18M, KT28G, KT28M, KT28N, KT30, KT30G, KT30J, KT30M, KT30N, TA36, TA51	0.024	J8C/130-093	B6S/130-781			
FG150, FG200, FG270, FG300	0.028	RL95YC/130-107				
KT10, KT12AD, KT12J, KT12K, KT15D, KT17, KT17J, TA33	0.024	CJ6/130-098	BM7A/130-864			
TEX54	0.026	RCJ6Y/130-073	BPMR7A/130-898		L7RTC/131-023	WSR6F/130-124
KOHLER						
Aegis Series liquid cooled						
LV560, LV625, LV630, LV675, LV680, LH630, LH685, LH690, LH750, LH755, LH775	0.030	RC14YC/130-530	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
Command/Command Pro Series						
CS4, CS6, CS8.5, CS10, CS12, CS12.75 Hydro, CS13 Hydro	0.030		BPR4ES/130-938			
CH16, CV460, CV490, CV492, CV493, CV17, CH18, CV18, CH20, CV20, CH22, CV22, CH23, CV23, CH25, CH270, CH395, CH730, CV730, CH26, CH27, CH740, CV740, CH745, CV745, CH750, CH940, CV940, CH960, CV960, CH980, CV980, CV1000	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	

* Net Priced Item

Spark Plug Application Chart

GAS ENGINES (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
KOHLER (Cont.)						
CH5, CH6, CH11, CH12.5, CH13, CH14, CH15, CV11, CV12.5, CV13, CV14, CV15	0.040	RC12YC/130-526		SE-12RCY/130-191	K5RTC/131-015	
Courage Series						
SV470, SV480, SV530, SV540, SV590, SV600, SV610, SV620, SV710, SV715, SV720, SV725, SV730, SV735, SV740, SV810, SV820, SV830, SV840	0.030	RC12YC/130-526	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
XT-6, XTR6, XT-7T	0.030	RA8HC/130-020		SE-12RCY/130-191	K5RTC/131-015	
XT-7, XTR-7	0.030	RA8HC/130-020	BKR5ES/130-906	SE-12RCY/130-191	K5RTC/131-015	
Magnum Series						
M8	0.025	RCJ8/130-091				
M10, M12, M14, M16, MV23	0.030		B6L/130-773			
MV16, M18, M18V, M20, MV20V	0.025	RV17YC/130-083	UR4/130-740			
Triad						
TH14, TH16, TH18	0.040	RC12YC/130-526		SE-12RCY/130-191	K5RTC/131-015	
K-Series						
K7, K12	0.025	RJ12C/130-087				
K90, K91, K121, K141, K161, L161, K181, L181, K330, K331, K660, K662	0.025	RJ19LM/130-106		SE-19J/130-211	G14C/131-007	WR11E0/130-108
K241, K301, K321, K341, K361, K482, K532, K582 (Twin)	0.0305		B6L/130-773			
KT17 (Twin), KT19 (Twin), KT20 (Twin), KT21 (Twin)	0.025	RV17YC/130-083	UR4/130-740			
KL25	0.030	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
LCT						
All engines	0.030				F6RTC/131-039	
SUBARU						
EC Series Air-Cooled 1 Cyl. 2-Stroke						
EC01ER, EC02ER, EC22GR, EC25GR	0.024	CJ6/130-098	BM7A/130-864			
EC03ER, EC04ER	0.024	CJ6Y/130-077				
EC05-2 D/B, EC06 D/B, EC07-2 D/B, EC08 D/B, EC25 D/DS	0.024	L86C/130-085				
EC12D, EC13V	0.024	CJ8/130-094				WS8E/130-112
EY Series Air-Cooled 1 Cyl 4-Stroke Side Valve						
EY08 D/BN	0.024	CJ14/130-097	BMR4A/130-756			
EY10 D/B, EY13-2 D/B, EY14 D/B, EY25 D/B, EY27-2 D/B	0.024	L86C/130-085				
EY15 D/DS, EY15-2 B, EY18-3 D/B, EY20 D/DS/B/BS	0.024		BR6HS/130-135			
EY23 D/DB/B/BS, EY35 D/DB/B/BS, EY40 D/DS/B/BS	0.024	RL95YC/130-107	BPR4HS/130-942			
EY28 D/DS/B/BS	0.024	L86C/130-085	BP6HS/130-272			
EY45V	0.024	RCJ8/130-079		SE-8JC/130-096	L6C/131-011	WS8E/130-112
EY Series Air-Cooled 2 Cyl. 4-Stroke Side Valve						
EY21 AS/AS-C, EY21 AS-R/AS-CR, EY80-3 AS/AS-C, EY80-3 AS-R/AS-CR	0.024	RL95YC/130-107	BPR4HS/130-942			
EH Series Air-Cooled 1 Cyl. 4-Stroke OHV						
EH025, EH035V	0.024		CMR6A/130-797			

* Net Priced Item

Spark Plug Application Chart

GAS ENGINES [Cont.]

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
SUBARU (Cont.)						
EH09, EH12 D/DS/B/BS, EH30 D/DS/B/BS, EH11, EH15, EH21	0.024		BR7ES/130-136			
EH17 D/DS/B/BS, EH25 D/DS/B/BS	0.024		BR6HS/130-135			
EH30 V/VS, EH34 V/VS	0.024	RN9YC/130-278	BPR6ES/130-823		F6RTC/131-039	
EH36, EH41, EH72	0.024		BPR5ES/130-930			
EX Series 4-Cycle OHC						
EX13, EX17, EX21, EX27, EX27 Fuel Injection, EX30, EX35, EX40	0.024		BR6HS/130-135			
TECUMSEH						
Horizontal 2-Stroke						
AH520, AH600, HXL840, TCH200	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
TCH300	0.030	RCJ6Y/130-073	BPMR7A/130-898			
Horizontal 4-Stroke						
H20	0.030		BPMR7A/130-898			
H22, H25, HT30, HT35, HXL35, HH40, HH50, HH60, HH70, HMXL70, HH80, HHM80, HH100, HSSK60, HSSK70	0.030	J8C/130-093				
H30, H35, H40, H50, H60, H70, H80, HM70, HM80, HM90, HM100, HS40, HS50	0.030	RCJ8/130-091	BR4LM/130-916	SE-8JC/130-096	L6C/131-011	WS8E/130-112
HMSK70, HMSK80, HMSK90, HMSK100	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	
WR11E0/130-108						
OH120, OH140, OH160	0.030		BR6HS/130-135			
OH180, OH195EA, OHH50, OHH55, OHH60, OHM120, OHSK50, OHSK55, OHSK110, OHSK120	0.030		BR7ES/130-136			
Vertical 2-Stroke						
TC200	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
TC300	0.030		BPMR7A/130-898			
TVS840, TVXL840	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	
WR11E0/130-108						
AV520, AV600, TVS600	0.028		BR4LM/130-916			
Vertical 4-Stroke						
ECV100, ECV105, ECV110, ECV115, ECV120, LV148, LV195EA, LEV100, LEV115, LEV120, TV275, TVS90, TNT100, TNT120, TVS100, TVS105, TVS115, TVS120, TVXL105, TVXL115	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	
WR11E0/130-108						
LAV25, LAV30, LAV35, LAV40, LAV50, OVM120, TVM125, TVM140, TVM170, TVXL170, V40, V50, V60, V70, V80, VH40, VH50, VH60, VH70, VH80, VH100, VM70, VM80, VM100	0.030	J8C/130-093				
OHV100, OHV110, OHV115, OHV120, OHV125, OHV130, OHV135, OHV14, OHV145, OHV15, OHV155, OHV16, OHV165, OHV17, OV195EA, OV350EA, OV490EA, OVRM35, OVRM40, OVRM50, OVRM55, OVRM60, OVRM65, OVRM905, OVXL125	0.030		BR7ES/130-136			

* Net Priced Item

Spark Plug Application Chart

GAS ENGINES (Cont.)

	PLUG GAP	CHAMPION	NGK	MEGA-FIRE	TORCH	BOSCH
TECUMSEH (Cont.)						
TVM195, TVM220, TVXL195, TVXL220, VLV40, VLV50, VLV55, VLV60, VLV65	0.030		BR4LM/130-916			
Snow King 2-Stroke						
HSK300, HSK600, HSK635, HSK840, HSK845, HSK850	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
HSK860, HSK870	0.030	RJ19LM/130-106	BR2LM/130-902	SE-19J/130-211	G14C/131-007	WR11E0/130-108
Snow King 4-Stroke						
HSK30, HSK35, HSK40, HSK40, HSK50, HSK50, HSK60, LH195SP, LH318SA, OH318SA, HSK60, HMSK70, HSK70, HMSK80, HMSK85, HMSK90, HMSK100, HMSK105, HMSK110	0.030	RJ19LM/130-106	BR2LM/130-902			
OHSK70, OHSK130	0.030		BR7ES/130-136			
TH098SA, TH139SA, TH139SP	0.030	RCJ8Y/130-079	BPMR6A/130-815		L6TC/131-027	
OHSK50, OHSK55, OH195SA, OHSK60, OHSK65, OH195SA, OHSK70, OH195SP, OHS75, OH318SA, OHSK80, OHSK90, OHSK100, OH318SA, OHSK110 (Spec. #223000 and higher), OHSK120 (Spec. #223000 and higher), OHSK130 (Spec. #223000 and higher)	0.030	RN4C/130-615				
OHSK110 (Spec. #222999 and lower), OHSK120 (Spec. #222999 and lower), OHSK130 (Spec. #222999 and lower)	0.030	L86C/130-085				
WISCONSIN-ROBIN						
Horizontal Shaft						
ECO2R	0.024	CJ6/130-098	BM7A/130-864			
EY18-3W, EY25W, EY27W, EY44W, W1-145, W1-185	0.024	L86C/130-085				
EY21W	0.024	J8C/130-093	B6S/130-781			
W1-080, W1-150	0.024	L86C/130-085	BP6HS/130-272			



Buy only what you need.

All spark plugs are sold individually.
Eliminate expensive inventory stock and order what you need, when you need it.

